

## D8C



SmartDisplay



Multipage display



SmartLabel



Plug & Play



USB port

### Stylish expansion module of the D8xx series

The Snom D8C is an expansion module for all devices in the D8xx series. The expansion module has a large, high-resolution colour display with a very clear user interface. Connected to the phone via USB via plug & play, the

Snom D8C expands the phones in the D8xx series with another large screen and a wide range of application options.

## Basics

- Product information
  - Expansion module D8C
    - gunmetal black (PN 00004562, EAN 4260059583534, UPC 811819013538)
    - white (PN 00004794, EAN 4262377562086, UPC 810100352080)
  - Operating system: Linux
- Placement: Indoor, desktop
- Daisy-chain up to 3 modules<sup>1</sup>

## Dimensions and weight

- Dimensions (L x W x D, approx.) without footstand
  - 210 mm x 140 mm x 43 mm
- Dimensions (H x W x D, approx.) with footstand (fix angle 40°)
  - 155 mm x 118 mm x 170 mm
- Weight (approx.)
  - 400 g without footstand
  - 455 g with footstand

## Display and indicators

- Display
  - TFT liquid crystal display (LCD), true colour, backlit
  - Size (diagonal): 6.86" (172 mm)
  - Size (W x H): 60 mm x 161 mm
  - Resolution: 1,280 x 480 pixels
- 23 LED indicators
  - Function key status indication: 20 multicolour LEDs
  - Page keys indication: 3 green LEDs

## Function keys

- 23 hard keys in total
  - 20 SmartLabel keys (with multicolour LED)
    - Key mapping of up to 60 functions (20 keys x 3 pages)

- 3 dedicated function keys: Page 1/2/3

## Interfaces and connections

- Power options
  - USB powering: 5 V
  - Power adapter:<sup>1</sup> 100 - 240 V AC, 50 - 60 Hz | 5 V DC (SELV), 2 A, 10 W
- Wired interfaces
  - Daisy chaining | USB powering | [USB headsets and other accessories](#)
    - USB 2.0 type A port
    - USB 2.0 type A plug
  - Power adapter:<sup>1</sup> coaxial power connector (socket)

## User interfaces and setup

- Plug & Play
- Completely configurable via host phone
- Customisation
  - Theme and icon support
  - Custom background image support

## Environmental conditions

- Operating ambient temperature
  - 0 °C - +35 °C
- Nonoperating (storage) temperature
  - -10 °C - +45 °C
- Humidity (non-condensing)
  - 5 % - 95 %

## Package contents

- Hardware
  - Expansion module D8C
  - Footstand
  - Screws
- Documentation
  - [Quick Installation Guide / Safety instructions](#)

## Snom accessories

- Power adapter<sup>1</sup> Snom 10 W PSU (PN 00004570)
- Power adapter<sup>3</sup> Snom 15 W PSU (PN 00004715)



## Compatible Snom devices

- IP desk phone (USB)<sup>2</sup>
  - D810W (PN 00004737, PN 00004792)
  - D812 (PN 00004690)
  - D815W (PN 00004691)
  - D815WB (PN 00004727, PN 00004793)
  - D862 (PN 00004535)
  - D865 (PN 00004536)



- D892M (PN 00004539)



- D895M (PN 00004540)



- DECT headset via USB A170C (PN 00004733)



- BT headset via Bluetooth dongle



- Monaural: A350M (PN 00004658)



- Binaural: A350D (PN 0000)

- Wired headset via USB



- Monaural: A330M (PN 00004597)



- Binaural: A330D (PN 00004598)

- **DECT USB dongle:** A230 (PN 00004386)



- **WLAN USB dongle** A210 (PN 00004384)



<sup>1</sup> When two or three modules are used with one phone, a separate power supply needs to be connected to the second module.

<sup>2</sup> Requires at least 10.1.180.0 firmware branch

<sup>3</sup> For D892M / D895M only

## Series overview



D8C



D812



D815W



D815WB



D862



D865



D892M



D895M

## Disclaimer

[Further information: D8C webpage](#) | [Snom Service Hub D8C](#) | [Quick Installation Guide D8C / Safety instructions D8C](#) | [Short User Manual D8C](#) | [Type approval](#) | [Warranty information](#) | [Company locations](#)

Snom, the names of Snom products, and Snom logos are trademarks owned by Snom Technology GmbH. All product specifications are subject to change without notification. Snom Technology GmbH reserves the right to revise and change this document at any time, without being obliged to announce such revisions or changes beforehand or after the fact. Although due care has been taken in the compilation and presentation of the information in this document, the data upon which it is based may have changed in the meantime. Snom therefore disclaims all warranties and liability for the accurateness, completeness, and currentness of the information published, except in the case of intention or gross negligence on the part of Snom or where liability arises due to binding legal provisions.